



Type

Order No.

FDM181

FDM181 Manual Call Point

S54321-F1-A1



The manual call point serves for the manual activation of alarms in case of fire. It consists of a housing and an electronic component.

- Resettable operation panel
- Automatically address setting without encoder setting or Dip-switch
- Indicates condition (Alarm or test) by means of an LED
- Communication via FD18-BUS
- "Sticker Method" for ease of commissioning

Operating voltage	12 ... 32 VDC
Operating current (quiescent)	0.22 mA
Activation current	1.2 mA
Operating temperature	-10 ... +50 °C
Storage temperature	-20 ... +75 °C
Humidity	≤95%
Communication protocol	FD18-BUS
Terminal block	1.0 ... 1.5 mm ²
Colour	Red, RAL3000
Protection category GB4208-93	IP44
Datasheet	A6V10214496